



V14 RANGE USER MANUAL



Hole Size

120mm Diameter +/- 5mm



Outlet Configuration

Standard Model:
4x Power Outlets
2x RJ45 Data Outlets
2x USB Power Outlets
Qi Wireless Charging Top



Model Options

Available in different options for different regions (US, UK, AU) and different outlet configurations (HDMI, USB RJ45)



Support

Contact your local distributor for support.
Manufactured by
Modern Power Solutions

INSTALLATION

1. Drill a hole in the required installation surface. The hole size diameter is indicated above in the model specifications.
2. Undo the mounting ring by spinning it clockwise with the unit pointing upside down.
3. Once the mounting ring is undone and removed from the unit, feed the power cable through the top of the installation hole, then place the unit inside this hole, so that it can fit flush with the bench-top.
4. Feed the mounting ring back through the cable, and tighten thoroughly to secure the unit to the bench-top.
5. Plug the power plug into an Australia power protected circuit.
6. The unit is ready for use. Press lightly on the lid of the unit to pop the lid up. Then pull on the lid to pull the model up completely. Push the unit back down to retract.

SPECIFICATIONS

Model designed for use in Australia and New Zealand.
Rated current of 10A, Rated voltage of 240v, or otherwise specified.
Earth connected, with shell earth contact.
Unit Also Features Cat6 Cables , & Qi Wireless Charging
USB Power Output 5v. Refer to the product tag for model specific specifications.